

BLU – 100 (12X8) MATRIZ DIGITAL DSP PADRÃO 19 POLEGADAS

DESCRIÇÃO

A **MATRIZ BLU 100** oferece uma configuração fixa de 12 entradas e 08 saídas, processamento de sinal configurável e um barramento de áudio digital de alta largura de banda e tolerante a falhas. Permite escolher qualquer configuração de entrada e saída que se adapte ao seu sistema específico - sem compromisso. Distribua o áudio multicanal sem interrupções entre várias unidades usando o cabo Cat.-5 e controle toda a capacidade de processamento da rede pela Ethernet.

Painéis de controle remoto para nível, predefinições. Ferramentas de diagnóstico integradas. Controle remoto da função via Ethernet. Programação de eventos.



CARACTERÍSTICAS

Construído para equipamentos padrão 19 polegadas
Matriz digital DSP

BLU – 100 (12X8)

MATRIZ DIGITAL DSP PADRÃO 19 POLEGADAS

ESPECIFICAÇÕES TÉCNICAS

OVERVIEW:

The Soundweb London BLU-100 offers a fixed configuration of 12 inputs and 8 outputs, configurable signal processing and a high bandwidth, fault tolerant digital audio bus.

The BLU-100 has open architecture which is fully configurable through HiQnet™ London Architect. A rich palette of processing and logic objects and a “drag and drop” method of configuration provide a simple and familiar design environment.

This processor features a low latency, fault tolerant digital audio bus of 48 channels which uses standard Category 5e cabling giving a distance of 100m between compatible devices. Fiber media converters can be used to increase the distance between devices to over 40km.

The BLU-100 is compatible with the entire Soundweb London family and its 48 channel digital audio bus represents channels 1-48 of the larger 256 channel digital audio bus when integrated with the BLU-800, BLU-320, BLU-160, BLU-120 and BLU-BOB devices.

Analog Inputs provide software configurable gain in 6dB steps up to +48dB per channel and software selectable Phantom Power per channel.

Phantom Power, Signal Present and Clip information per channel is easily accessible, without the requirement for a PC, from clear front panel LED indication. A bi-directional locate function allows devices to be identified both from and within HiQnet London Architect.

12 Control Inputs and 6 Logic Outputs allow the BLU-100 to be integrated with GPIO compatible devices. The Soundweb London Interface Kit, comprehensive documentation which details how Soundweb London systems can be integrated with third party control systems, is included within the installation of HiQnet London Architect.

The BLU-100 and the other members of the Soundweb London family provide the building blocks of the perfectly tailored system solution.

KEY FEATURES:

- 12 Analog Inputs (with 48v Phantom Power per Channel)
- 8 Analog Outputs
- Configurable Signal Processing
- Rich Palette of Processing and Logic Objects
- 48 Channel, Low Latency, Fault Tolerant Digital Audio Bus
- Clear Front Panel LED Indication
- Bi-Directional Locate Functionality
- 12 Control Inputs and 6 Logic Outputs for GPIO Integration
- Soundweb London Interface Kit for Third Party Control System Integration (Documentation)
- HiQnet Device
- Configuration, Control and Monitoring from HiQnet London Architect

BLU – 100 (12X8)

MATRIZ DIGITAL DSP PADRÃO 19 POLEGADAS

ESPECIFICAÇÕES TÉCNICAS

Front Panel Led Indicators:

Per Input: Signal Present, CLIP, 48V (Input only)

Other: COM, STAT, ERR, PWR

Analog Inputs: 12 electronically balanced on Phoenix Combicon removable screw connectors

Mic/Line Inputs: Nominal gain 0dB, electronically switchable up to +48dB, in +6dB steps

Input Impedance: 3.5k Ω

Maximum Input Level: +20dBu with 0dB input gain, +8dBu with 12dB gain

CMRR: >75dB at 1KHz

Input Noise (E.I.N.): <-128dBu typical with 150 Ω source

Phantom Power: 48V nominal, selectable per input

A/D Latency: 37/Fs [0.77ms@48k]

Analog Outputs: 8 electronically balanced on Phoenix/Combicon removable screw connectors

Maximum Output Level: +19dBu

Frequency Response: 20Hz-20KHz (+0.5dB/-1dB)

THD: <0.01% 20Hz to 20KHz, +10dBu output

Dynamic Range: 108dB typical, 22Hz-22KHz unweighted

Crosstalk: <-75dB

Output Impedance: 40 Ω balanced and 20 Ω unbalanced

D/A Latency: 29/Fs [0.60ms@48k]

Control Ports: 12 inputs and 6 outputs

Control Input Voltage: 0 to 4.5v

Control Input Impedance: 4.7k Ω to +5V (2-wire mode), >1M Ω (3-wire mode)

Logic Output Voltage: 0 or +5V unloaded

Logic Output Impedance: 440 Ω

Logic Output Current: 10mA source, 60mA sink

Watchdog Output: Phoenix/Combicon connector for failsafe control

Opto Output Current: 14mA maximum

Withstanding Voltage: 80V maximum (Off)

Series Impedance: 220 Ω (isolated)

Control Network:

Connectors: RJ45 Ethernet connector

Maximum Cable Length: 100m/300ft on Category 5 cable between device and Ethernet switch

BLU link:

Connectors: 2 x RJ45 Ethernet connectors

Maximum Cable Length: 100m/300ft on Category 5e cable between devices

Max. Number of Nodes: 60

Latency: 11/Fs [0.23ms@48k]

Pass Through Latency: 4/Fs [0.08ms@48k]

Power and Dimensions:

Mains Voltage: 100-240V AC, 50/60Hz

Power Consumption: <55VA

BTU Rating: <188 BTU/hr

Operating Temp. Range: 0 $^{\circ}$ to 45 $^{\circ}$ C (32 $^{\circ}$ to 113 $^{\circ}$ F)

Dims: (H(U) x W x D): 1.75" (1U) x 19" x 9.0" (45mm x 483mm x 229mm)

Weight: 6.4 lbs / 2.9 kg

Conforme Lei Federal n $^{\circ}$ 11.291/06, informamos que a exposição prolongada a ruídos superiores a 85 decibéis pode causar danos ao sistema auditivo. A **DI-SOM** não se responsabiliza pelo uso inadequado dos seus produtos.

DEPARTAMENTO DE ENGENHARIA E SISTEMAS ESPECIAIS.



DI-SOM PRODUTOS ELETRÔNICOS

Rua Sava, 37 – Sacomã.

São Paulo – SP - 04283-020

Fone: 11 3806-4040

www.di-som.com.br



Todos os produtos da **DI-SOM** são continuamente aprimorados. Todas as especificações estão sujeitas a alterações sem prévio aviso.
Copyright © 2019 **DI-SOM**. Todos os direitos reservados